

---

**Python**  
*Release 1.0.3*

Apr 06, 2017



---

## Contents

---

<b>1 API Documentation</b>	<b>3</b>
1.1 modbusreader . . . . .	3
1.2 modbusreader.structutils . . . . .	5
<b>2 Indices and tables</b>	<b>7</b>
<b>Python Module Index</b>	<b>9</b>



Contents:



# CHAPTER 1

---

## API Documentation

---

### modbusreader

```
class modbusreader.ModbusReader(host, port, unit, modbus_device_definition,  
                                float_low_byte_first=False)
```

Bases: `object`

ModbusReader is an automated modbus client which reads all discretes and registers of a modbus server over TCP

```
__init__(host, port, unit, modbus_device_definition, float_low_byte_first=False)  
    Initializes a new instance
```

#### Parameters

- **host** (`str`) – host of modbus server
- **port** (`int`) – port of modbus server
- **unit** (`int`) – unit id
- **modbus\_device\_definition** (`dict or str`) – modbus device definition python dictionary or file name based on config [https://github.com/smueler18/modbus-readermodbusreader/modbus\\_definition.config.json](https://github.com/smueler18/modbus-readermodbusreader/modbus_definition.config.json)
- **float\_low\_byte\_first** (`bool`) – Because modbus float datatype consists of two integer bytes, there are 2 possibilities for the determination of the float value. Set to True if float interpretation order is Low Byte and then High Byte. Otherwise interpretation order is High Byte and then Low Byte.

#### Raises

- **ValidationError** – if the modbus device definition dictionary or file is invalid
- **SchemaError** – if the modbus device definition config itself is invalid

#### \_\_weakref\_\_

list of weak references to the object (if defined)

```
static group_modbus_device_definition(modbus_device_definition)
Groups modbus addresses. This method is needed, if there are gaps of non existent modbus addresses.

Parameters modbus_device_definition (dict) – modbus device definition dictionary

Returns grouped modbus device definition dictionary

Type dict

read_all_values()
read discretes and registers

Returns discrete output values as follows: { sensor_id: sensor_value, ... }

Type dict

Raises IOError – is raised if reading discretes or registers over TCP connection fails

read_discrete_inputs()
read discrete inputs

Returns discrete output values as follows: { sensor_id: sensor_value, ... }

Type dict

Raises IOError – is raised if reading discretes over TCP connection fails

read_discrete_outputs()
read discrete outputs

Returns discrete output values as follows: { sensor_id: sensor_value, ... }

Type dict

Raises IOError – is raised if reading discretes over TCP connection fails

read_discretes(discrete_type)
read either discrete inputs or outputs

Parameters discrete_type (str) – type of discrete. either ‘input’ or ‘output’

Returns discrete values: { sensor_id: sensor_value, ... }

Type dict

Raises

• AttributeError – is raised if discrete_type doesn’t match required types
• IOError – is raised if reading discretes over TCP connection fails

read_input_registers()
read input registers

Returns discrete output values as follows: { sensor_id: sensor_value, ... }

Type dict

Raises IOError – is raised if reading registers over TCP connection fails

read_output_registers()
read output registers

Returns discrete output values as follows: { sensor_id: sensor_value, ... }

Type dict

Raises IOError – is raised if reading registers over TCP connection fails
```

**read\_registers**(register\_type)

read either input or output registers

**Parameters** **register\_type**(*str*) – type of register. either ‘input’ or ‘output’**Returns** discrete output values as follows: { sensor\_id: sensor\_value, ... }**Type** dict**Raises**

- **AttributeError** – If register\_type doesn’t match required types

- **IOError** – If reading registers over TCP connection fails

## modbusreader.structutils

structutils.py: extends the function of the struct package

**modbusreader.structutils.bytes\_to\_datatype**(byte\_list, data\_type)

Unpacks a bytes object to the given data type

**Parameters**

- **byte\_list**(*bytes*) – bytes object
- **data\_type**(*str*) – human readable data type. One of: int16, int32, uint32, float, byte, boolean

**Returns** unpacked value**Type** int, float, byte, boolean**Raises** **ValueError** – If size of data type is not equal to the size of the bytes object.**modbusreader.structutils.calcsize**(data\_type)

Return size in bytes of the struct described by the given data type

**Parameters** **data\_type**(*str*) – human readable data type. One of: int16, int32, uint32, float, byte, boolean**Returns** size in bytes of the struct described by the given data type**Type** int**modbusreader.structutils.get\_format**(data\_type)

Get struct format type from human readable data type

**Parameters** **data\_type**(*str*) – human readable data type. One of: int16, int32, uint32, float, byte, boolean**Returns** struct format type**Type** str**modbusreader.structutils.int16list\_to\_bytes**(int16\_list)

Packs all given integer values into bytes object

**Parameters** **int16\_list**(*list of int*) – list containing unsigned 16 bit integers**Returns** packed integer values**Type** bytes



## CHAPTER 2

---

### Indices and tables

---

- genindex
- modindex
- search



---

## Python Module Index

---

### m

`modbusreader`, 3  
`modbusreader.structutils`, 5



### Symbols

`__init__()` (modbusreader.ModbusReader method), 3  
`__weakref__` (modbusreader.ModbusReader attribute), 3

### B

`bytes_to_datatype()` (in module modbusreader.structutils), 5

### C

`calcsize()` (in module modbusreader.structutils), 5

### G

`get_format()` (in module modbusreader.structutils), 5  
`group_modbus_device_definition()` (modbusreader.ModbusReader static method), 3

### I

`int16list_to_bytes()` (in module modbusreader.structutils), 5

### M

ModbusReader (class in modbusreader), 3  
modbusreader (module), 3  
modbusreader.structutils (module), 5

### R

`read_all_values()` (modbusreader.ModbusReader method), 4  
`read_discrete_inputs()` (modbusreader.ModbusReader method), 4  
`read_discrete_outputs()` (modbusreader.ModbusReader method), 4  
`read_discretes()` (modbusreader.ModbusReader method), 4  
`read_input_registers()` (modbusreader.ModbusReader method), 4  
`read_output_registers()` (modbusreader.ModbusReader method), 4  
`read_registers()` (modbusreader.ModbusReader method), 4